


# isc Three Terminal Positive Voltage Regulator

## MC7812E

### **FEATURES**

- · Output current in excess of 1 A
- Output voltage of 12V
- · Internal thermal overload protection
- Output transition Safe-Area compensation
- 100% avalanche tested
- Minimum Lot-to-Lot variations for robust device performance and reliable operation




### ABSOLUTE MAXIMUM RATINGS(Ta=25℃)

SYMBOL	PARAMETER	RATING	UNIT	
Vi	DC input voltage	35	V	
Io	Output current	internally limited		
P <sub>tot</sub>	Power dissipation	internally limited	9	
Тор	Operating junction temperature	-40~125	°C	
T <sub>stg</sub>	Storage temperature	-55~150	$^{\circ}$	

### THERMAL CHARACTERISTICS

SYMBOL	PARAMETER	MAX	UNIT
R <sub>th j-c</sub>	Thermal Resistance, Junction to Case	5	°C/W
R <sub>th j-a</sub>	Thermal Resistance,Junction to Ambient	65	°C/W



## isc Three Terminal Positive Voltage Regulator

MC7812E

#### ELECTRICAL CHARACTERISTICS

T<sub>j</sub>=25°C (V<sub>i</sub>= 19V, I<sub>0</sub>=0.5A, C<sub>i</sub>= 0.33  $\mu$  F, C<sub>0</sub>= 0.1  $\mu$  F unless otherwise specified)

SYMBOL	PARAMETER	CONDITIONS	MIN	MAX	UNIT
Vo	Output Voltage	V <sub>in</sub> =19V; I <sub>O</sub> =500mA	11.5	12.5	V
Vo	Output Voltage	I <sub>O</sub> =5 mA to 1A;Po≤15W; V <sub>in</sub> =14.5 to 27V;	11.4	12.6	V
$\triangle V_V$	Line Regulation	14.5V≤V <sub>in</sub> ≤30V 16V≤V <sub>in</sub> ≤22V		240 120	mV
$\triangle V_i$	Load Regulation	5.0mA≤I <sub>O</sub> ≤1.0 A 250mA≤I <sub>O</sub> ≤750mA		240 120	mV
I <sub>b</sub>	Quiescent Current	V <sub>in</sub> =19V; I <sub>O</sub> =0.5A		8.0	mA
$\triangle$ b1	Quiescent Current Change	5.0mA≤I <sub>0</sub> ≤1.0A		0.5	mA
$\triangle_{ t b2}$	Quiescent Current Change	14.5V≤V <sub>in</sub> ≤30V		1.0	mA

#### NOTICE:

ISC reserves the rights to make changes of the content herein the datasheet at any time without notification. The information contained herein is presented only as a guide for the applications of our products.

ISC products are intended for usage in general electronic equipment. The products are not designed for use in equipment which require specialized quality and/or reliability, or in equipment which could have applications in hazardous environments, aerospace industry, or medical field. Please contact us if you intend our products to be used in these special applications. ISC makes no warranty or guarantee regarding the suitability of its products for any particular purpose, nor does ISC assume any liability arising from the application or use of any products, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages.